


Wskaźnik dostrojenia

EM 80


Telefunken

Dla odbiorników AM

Nowal



$$\frac{U_z = 6,3 \text{ V}}{I_z = 300 \text{ mA}}$$



Wartości robocze

U_{ab}	250	200	V
U_L	250	200	V
R_a	0,5	0,5	MΩ
R_s	3	—	MΩ
U_s	—1...—20	0...—16	V
γ	0... 26°	0... 26°	
I_a	480... 50	380... 40	μA
I_L	2... 2,3	1,5... 2,7	mA

Wartości graniczne

U_{a0max}	550	V
U_{amax}	300	V
P_{amax}	0,2	W
U_{L0max}	550	V
U_{L0min}	165	V
U_{smax}	—1,3	V
I_{kmax}	3	mA
R_{smax}	3	MΩ
U_w/k_{max}	100	V
R_w/k_{max}	20	kΩ

¹⁾ $I_s = +0,3 \mu\text{A}$

TYPY PODOBNE

6 BR 5, 6 M 40 (Tesla) 6 E 1 Π

