







T.			U_f	I_f	U_o	U_g	I_o	S	μ	R_i
			V	A	V	V	mA	mA/V	V/V	k Ω
C 509 A	Phl amer	1	5	0,25	150	-10	10	1	9	9
12 A		2	5	0,25	180	-13,5	7,7	1,8	8,5	4,7

Equivalents

BF-O T. Fot = C 509 A	R 29 Dar = C 509 A	G 112 amer = 12 A
CA 201 A Cas = C 509 A	U 525 Val = C 509 A	NX 112 A amer = 12 A
CX 201 A Cas = C 509 A	112 A RCA = 12 A	PX 1120 Tu = 12 A



T.			U_f	I_f	U_a	U_g	I_a	S	μ	R_i	R_o	P_o
			V	A	V	V	mA	mA/V	V/V	k Ω	k Ω	W
71	amer	1	5	0,5	90	- 16,5	10	1,4	3	2,17	3	0,125
71-A	amer	1	5	0,25	135	- 27	17,3	1,65	3	1,82	3	0,4
71-B	amer	1	5	0,125	180	- 40,5	20	1,7	3	1,75	4,8	0,79