

Pentoda

EL 171

RFT


Wzmacniacz mocy m. cz.

Loktal

EL171

$$\frac{U_z}{I_z} = 6,3 V$$

$$I_z = 0,9 A$$



Wartości robocze

| | | |
|-----------|-----|-----------------|
| U_a | 250 | V |
| I_a | 40 | mA |
| U_{s1} | -12 | V |
| U_{s2} | 250 | V |
| U_{s3} | 0 | V |
| I_{s2} | 6 | mA |
| S_a | 9 | mA/V |
| ρ_a | 17 | k Ω |
| R_a | 4 | k Ω |
| R_k | 260 | Ω |
| P_a | 10 | W |
| P_{wyj} | 4,5 | W |
| U_{wej} | 4,5 | V _{sk} |

TYPY PODOBNE

EL 84