


Pentoda

PL 83


Telefunken

Wzmacniacz końcowy toru wizji (TV)

Nowal



$U_z = 15V$
 $I_z = 300mA$



Wartości robocze

U_{i4}	170	200	V
U_{s3}	0	0	V
U_{s2}	170	200	V
U_{s1}	-2,3	-3,5	V
I_{i4}	36	36	mA
I_{s2}	5	5	mA
$K_{s2/s1}$	24	24	V/V
S_{i2}	10,5	10,5	mA/V
ρ_a	0,1	0,1	M Ω

Wartości graniczne

U_{a0max}	550	V
U_{dmax}	250	V
U_{s20max}	550	V
U_{s2max}	250	V
U_{s1max}	-1,3	V ¹⁾
U_{zmax}	22,5	V
P_{dmax}	9	W
P_{s2max}	2	W
I_{kmax}	70	mA
$R_{s1max}(stały)$	0,5	M Ω
$R_{s1max}(aut.)$	1	M Ω
$U_{w/kmax}$	150	V
$R_{w/kmax}$	20	k Ω

Pojemności

C_{wej}	10,4	pF
C_{wyf}	6,6	pF
$C_{s/a}$	<0,1	pF
$C_{s/w}$	<0,15	pF

¹⁾ $I_{s1} = +0,3 \mu A$

TYPY PODOBNE

15 A 6, N 309 (Marconi)

