





Rectifiers, General Purpose

1.0 to 3.0 Amperes

200 to 1000 Volts

I_O (AMPS)	1.0		2.0	3.0
@ T_A (°C)	25	25	25	25
I_{FSM} (AMPS)	30	30	60	200
CASE	 SMA	 SMB		 SMC
V_{RRM} (VOLTS)				
200	CMR1-02M	CMR1-02	CMR2-02	CMR3-02
400	CMR1-04M	CMR1-04	CMR2-04	CMR3-04
600	CMR1-06M	CMR1-06	CMR2-06	CMR3-06
1000	CMR1-10M	CMR1-10	CMR2-10	CMR3-10

V_F MAX @ $I_F = I_O$	1.1V	1.1V	1.1V	1.2V
-------------------------	------	------	------	------

I_R MAX @ V_{RRM}	5.0 μ A	10 μ A	0.5 μ A	5.0 μ A
-----------------------	-------------	------------	-------------	-------------