


Trioda


7B4

Wzmacniacz oporowy

Loktal



$U_z \sim 6,3 V$
 $I_z \sim 0,3 A$



Wartości robocze

U_a	100	250	V
U_a	-1	-2	V
I_a	0,4	0,9	mA
K_a	100	100	V/V
S_a	1,15	1,5	mA/V
a_k	85	66	k Ω
qR	2,5	2,2	k Ω

Wartości maksymalne

U_{amax}	300	V
P_{amax}	1,5	W
R_{smax}	1	M Ω

Pojemności

C_{wej}	3,5	pF
C_{wyj}	2,8	pF

TYPY PODOBNE

6 F 5, 6 SF 5