

Pentoda

**EL 150**


Telefunken

Wzmacniacz mocy

Stalowy

*EL150*

$$\frac{U_{\dot{z}} = 6,3 V}{I_{\dot{z}} = 1,2 A}$$



Wartości charakterystyczne i robocze

Wartości graniczne

$U_a$	350	V
$U_{s2}$	350	V
$U_{s1}$	-14	V
$I_a$	110	mA
$I_{s2}$	14	mA
$S_a$	12	mA/V
$\rho_a$	50	k $\Omega$
$R_a$	5	k $\Omega$
$R_k$	250	$\Omega$
$P_a$	32	W

$U_{abmax}$	350	V
$P_{amax}$	32	W

TYPY PODOBNE

**EL 12/350**